

DDJ-RB

Hardware Diagram for rekordbox dj



GROUP No.	NAME	FUNCTION	+SHIFT
BROWSER			
1	LOAD	Left	Load track (Double click) Inst. Doubles
		Right	Load track (Double click) Inst. Doubles
2	BROWSE	Rotate	Track/Folder Select
		Push	Move to track list
DECK			
3	TEMPO	Tempo Control	
4	JOG	Top of jog	Scratch
		Side of jog	Pitch Bend
5	LOOP IN	Normal	Loop in
		Long press	4 BEAT Loop
6	LOOP OUT	Loop out	RE-TRIGGER
7	PLAY/PAUSE	Play/Pause	
8	CUE	Set Cue/Play, Back Cue	Jump to track start
9	SYNC	Sync	Master
10	SHIFT	Shift	-
MIXER			
11	TRIM	Trim	
12	EQ (HI, MID, LOW)	EQ (High, Mid, Low)	
13	FILTER	Filter	
14	MASTER LEVEL	Master Level	
15	HEADPHONES LEVEL	Headphones Level	
16	MASTER CUE	Master Cue	Panel display on/off
17	HEADPHONES CUE	Headphones Cue	Tap BPM
18	CH FADER	Channel fader	Channel fader start
19	CROSSFADER	Crossfader	Crossfader start
20	MIC LEVEL	Mic Level	

GROUP No.	NAME	FUNCTION	+SHIFT
EFFECT			
21	FX	Beat FX On/Off. Switch parameter	Beat FX select
22	BEAT (◀)	FX beat down	FX Auto Beat
23	BEAT (▶)	FX beat up	FX TAP (Adjust tempo manually)
24	LEVEL/DEPTH	Beat FX parameter adjustment	
PERFORMANCE PADS			
25	HOT CUE	Normal	Hot Cue Mode
		press twice	Active Censor Mode
26	PAD FX 1	PAD FX1 Mode	PAD FX2 Mode
27	PAD FX 2	Slicer Mode	Slicer Loop Mode
28	SAMPLER	Sampler Mode	Sequence Call Mode
PERFORMANCE PAD 1-8			
29 to 36	mode	Hot Cue	Hot cue
		Beat Jump	Beat Jump
		PAD FX1	PAD FX1 ON (Momentary)
		PAD FX2	PAD FX2 ON (Momentary)
		Slicer	Slicer
		Slicer Loop	Slicer Loop
		Sampler	Sampler Stop
		Active Censor	Select FX(1-8), Renge Specification(5-7), On/Off(8)
Sequence Call	Sequence Play		

Change history

1st edition	April 21, 2016	
2nd edition	February 6, 2017	Addition [6,PERFORMANCE PADS] ·[9,Hot Cue] [press twice] [Active Censor Mode] ·[1 to 8,PERFORMANCE PAD 1-8] [Active Censor], [Select FX(1-8),Renge Specification(5-7),On/Off(8)]